

## Feuille1

Type	Section	MH	RDC ohm	Diamètre	Poids (g)
Cross Coil	14 AWG	<b>0,011</b>	0,021	31	73
Cross Coil	14 AWG	<b>0,018</b>	0,026	33	115
Cross Coil	14 AWG	<b>0,022</b>	0,030	33	115
Cross Coil	14 AWG	<b>0,025</b>	0,033	34	117
Cross Coil	14 AWG	<b>0,028</b>	0,035	34	117
Cross Coil	14 AWG	<b>0,030</b>	0,035	35	120
Cross Coil	14 AWG	<b>0,050</b>	0,050	36	136
Cross Coil	14 AWG	<b>0,080</b>	0,060	40	165
Cross Coil	14 AWG	<b>0,090</b>	0,063	41	173
Cross Coil	14 AWG	<b>0,100</b>	0,070	42	181
Cross Coil	14 AWG	<b>0,110</b>	0,075	43	189
Cross Coil	14 AWG	<b>0,120</b>	0,078	44	197
Cross Coil	14 AWG	<b>0,150</b>	0,087	45	219
Cross Coil	14 AWG	<b>0,160</b>	0,082	46	219
Cross Coil	14 AWG	<b>0,180</b>	0,095	46	232
Cross Coil	14 AWG	<b>0,200</b>	0,100	47	248
Cross Coil	14 AWG	<b>0,220</b>	0,105	49	264
Cross Coil	14 AWG	<b>0,240</b>	0,115	50	275
Cross Coil	14 AWG	<b>0,250</b>	0,116	50	280
Cross Coil	14 AWG	<b>0,270</b>	0,120	51	296
Cross Coil	14 AWG	<b>0,300</b>	0,125	51	318
Cross Coil	14 AWG	<b>0,310</b>	0,126	52	325
Cross Coil	14 AWG	<b>0,330</b>	0,128	52	330
Cross Coil	14 AWG	<b>0,350</b>	0,129	54	342
Cross Coil	14 AWG	<b>0,360</b>	0,131	53	348
Cross Coil	14 AWG	<b>0,380</b>	0,135	54	360
Cross Coil	14 AWG	<b>0,390</b>	0,139	55	366
Cross Coil	14 AWG	<b>0,400</b>	0,142	56	372
Cross Coil	14 AWG	<b>0,410</b>	0,147	56	378
Cross Coil	14 AWG	<b>0,440</b>	0,160	57	394
Cross Coil	14 AWG	<b>0,470</b>	0,165	58	407
Cross Coil	14 AWG	<b>0,480</b>	0,167	58	409
Cross Coil	14 AWG	<b>0,500</b>	0,170	58	423
Cross Coil	14 AWG	<b>0,510</b>	0,172	58	428
Cross Coil	14 AWG	<b>0,520</b>	0,174	59	432
Cross Coil	14 AWG	<b>0,530</b>	0,175	59	437
Cross Coil	14 AWG	<b>0,560</b>	0,177	60	448
Cross Coil	14 AWG	<b>0,590</b>	0,182	61	463
Cross Coil	14 AWG	<b>0,600</b>	0,183	61	468
Cross Coil	14 AWG	<b>0,620</b>	0,190	62	490
Cross Coil	14 AWG	<b>0,660</b>	0,188	62	512
Cross Coil	14 AWG	<b>0,680</b>	0,196	63	538
Cross Coil	14 AWG	<b>0,700</b>	0,201	64	546
Cross Coil	14 AWG	<b>0,710</b>	0,203	64	550
Cross Coil	14 AWG	<b>0,720</b>	0,205	64	555
Cross Coil	14 AWG	<b>0,730</b>	0,205	64	555
Cross Coil	14 AWG	<b>0,750</b>	0,206	64	559
Cross Coil	14 AWG	<b>0,770</b>	0,208	64	562
Cross Coil	14 AWG	<b>0,780</b>	0,210	65	565

Feuille1

Cross Coil	14 AWG	<b>0,790</b>	0,212	65	568
Cross Coil	14 AWG	<b>0,800</b>	0,214	66	571
Cross Coil	14 AWG	<b>0,810</b>	0,217	66	574
Cross Coil	14 AWG	<b>0,820</b>	0,220	66	577
Cross Coil	14 AWG	<b>0,830</b>	0,222	66	580
Cross Coil	14 AWG	<b>0,850</b>	0,224	67	584
Cross Coil	14 AWG	<b>0,870</b>	0,226	67	588
Cross Coil	14 AWG	<b>0,890</b>	0,228	67	592
Cross Coil	14 AWG	<b>0,900</b>	0,230	67	594
Cross Coil	14 AWG	<b>0,910</b>	0,235	68	596
Cross Coil	14 AWG	<b>0,920</b>	0,237	69	598
Cross Coil	14 AWG	<b>0,930</b>	0,238	69	600
Cross Coil	14 AWG	<b>0,940</b>	0,240	69	602
Cross Coil	14 AWG	<b>0,950</b>	0,241	69	604
Cross Coil	14 AWG	<b>0,970</b>	0,245	69	608
Cross Coil	14 AWG	<b>0,980</b>	0,247	69	610
Cross Coil	14 AWG	<b>0,990</b>	0,248	69	612
Cross Coil	14 AWG	<b>1,000</b>	0,250	70	614
Cross Coil	14 AWG	<b>1,050</b>	0,255	70	618
Cross Coil	14 AWG	<b>1,070</b>	0,258	70	620
Cross Coil	14 AWG	<b>1,100</b>	0,260	71	646
Cross Coil	14 AWG	<b>1,150</b>	0,265	72	662
Cross Coil	14 AWG	<b>1,200</b>	0,270	72	678
Cross Coil	14 AWG	<b>1,250</b>	0,275	72	694
Cross Coil	14 AWG	<b>1,270</b>	0,278	72	700
Cross Coil	14 AWG	<b>1,280</b>	0,280	73	704
Cross Coil	14 AWG	<b>1,300</b>	0,285	74	710
Cross Coil	14 AWG	<b>1,350</b>	0,290	75	726
Cross Coil	14 AWG	<b>1,400</b>	0,295	76	742
Cross Coil	14 AWG	<b>1,430</b>	0,297	76	749
Cross Coil	14 AWG	<b>1,450</b>	0,299	77	765
Cross Coil	14 AWG	<b>1,500</b>	0,305	77	770
Cross Coil	14 AWG	<b>1,600</b>	0,330	78	797
Cross Coil	14 AWG	<b>1,700</b>	0,335	79	824
Cross Coil	14 AWG	<b>1,750</b>	0,340	80	838
Cross Coil	14 AWG	<b>1,800</b>	0,355	81	850
Cross Coil	14 AWG	<b>1,900</b>	0,370	82	875
Cross Coil	14 AWG	<b>2,000</b>	0,380	83	900
Cross Coil	14 AWG	<b>2,100</b>	0,400	84	924
Cross Coil	14 AWG	<b>2,200</b>	0,420	84	946
Cross Coil	14 AWG	<b>2,300</b>	0,430	85	968
Cross Coil	14 AWG	<b>2,400</b>	0,434	86	992
Cross Coil	14 AWG	<b>2,500</b>	0,438	87	1015
Cross Coil	14 AWG	<b>2,550</b>	0,427	87	1027
Cross Coil	14 AWG	<b>2,600</b>	0,442	88	1038
Cross Coil	14 AWG	<b>2,700</b>	0,445	89	1060
Cross Coil	14 AWG	<b>2,800</b>	0,455	90	1095
Cross Coil	14 AWG	<b>2,900</b>	0,465	91	1130
Cross Coil	14 AWG	<b>3,000</b>	0,475	92	1165
Cross Coil	14 AWG	<b>3,300</b>	0,500	94	1200

Feuille1

Cross Coil	14 AWG	<b>3,750</b>	0,540	98	1305
Cross Coil	14 AWG	<b>3,900</b>	0,550	99	1340
Cross Coil	14 AWG	<b>4,000</b>	0,555	100	1387
Cross Coil	14 AWG	<b>4,200</b>	0,560	104	1412
Cross Coil	14 AWG	<b>4,600</b>	0,580	105	1500
Cross Coil	14 AWG	<b>4,700</b>	0,600	105	1510
Cross Coil	14 AWG	<b>4,800</b>	0,620	105	1533
Cross Coil	14 AWG	<b>5,000</b>	0,640	106	1581
Cross Coil	14 AWG	<b>5,500</b>	0,650	109	1679
Cross Coil	14 AWG	<b>5,600</b>	0,660	109	1693
Cross Coil	14 AWG	<b>5,700</b>	0,700	110	1645
Cross Coil	14 AWG	<b>6,000</b>	0,690	111	1715
Cross Coil	14 AWG	<b>6,200</b>	0,700	113	1800
Cross Coil	14 AWG	<b>6,500</b>	0,730	114	1820
Cross Coil	14 AWG	<b>6,600</b>	0,745	115	1856
Cross Coil	14 AWG	<b>6,750</b>	0,765	117	1917
Cross Coil	14 AWG	<b>6,800</b>	0,770	117	1937
Cross Coil	14 AWG	<b>7,000</b>	0,780	118	1950
Cross Coil	14 AWG	<b>7,200</b>	0,788	120	1960
Cross Coil	14 AWG	<b>7,500</b>	0,800	120	2060
Cross Coil	14 AWG	<b>8,000</b>	0,850	123	2076
Cross Coil	14 AWG	<b>8,200</b>	0,870	124	2082
Cross Coil	14 AWG	<b>9,000</b>	0,910	125	2225
Cross Coil	14 AWG	<b>9,100</b>	0,920	125	2215
Cross Coil	14 AWG	<b>10,000</b>	0,940	132	2440
Cross Coil	14 AWG	<b>12,000</b>	1,100	136	2760
Cross Coil	14 AWG	<b>13,000</b>	1,150	141	2860
Cross Coil	14 AWG	<b>15,000</b>	1,230	149	3060
Cross Coil	14 AWG	<b>18,000</b>	1,390	152	3410
Cross Coil	14 AWG	<b>20,000</b>	1,500	157	3660